

BH260



Adaptive Video Equaliser, automatic receiver for correction of up to 1mile (1.6km) with Cat5e/6 Unshielded and Shielded cable

Overview

The BH260 unit positioned at the receiving end of the cable will automatically correct a video signal at the push of a button and deliver a high quality video signal over Cat5e/6 cable of up to 1 mile (1.6km). 4

passive baluns are supplied free of charge to be fitted at the camera end of the cable run. A 12V DC power supply is also included. Can be cabinet mounted or fixed to a panel or wall.



- Fully automatic, no user adjustment required
- Automatic polarity detection and inversion
- Automatically restores settings on power up
- Simple and quick installation
- Automatic cable type compensation
- Low power consumption
- No set-up test equipment required
- Lifetime Warranty

Technical Information

INPUT SIGNAL TYPE	Balanced composite video signal. NTSC or PAL
INPUT IMPEDANCE	100 Ohm
OUTPUT SIGNAL	1.0V Pk-Pk @ 75 Ohm
SIGNAL INPUT CONNECTOR	4 x Spring-loaded connector, maximum cable size 1.5mm ²
SIGNAL OUTPUT CONNECTOR	4 x BNC male type coax connector
AT UNITY GAIN	Differential Phase < 1.0° Differential Gain < 1%
BANDWIDTH	40Hz to 6MHZ
PERFORMANCE	Will equalise a video signal on the following cable types: Cat5e/6 Unshielded Twisted Pair up to 1 mile (1.6km) Cat5e/6 Shielded Twisted Pair up to 1 mile (1.6km) Standard BT Cable 1/2 mile (800m) *If you have a specific cable you would like us to test, please contact us at the address below.
POLARITY DETECTION	Automatic detection & correction of inverted input
SURGE PROTECTION	Transorbs and gas tubes fitted as standard
POWER REQUIREMENTS	12V DC @ 450mA
POWER SUPPLY	Included, international plug top switch-mode regulated power supply 90 – 265Vac power consumption nominally 13 Watts. Supplied with 'country specific' input connector.
OPERATING TEMP. RANGE	-30 to +45 degrees Celsius
CONTROLS	Auto setup button
INDICATOR LED's	Blue LED indicates power Yellow LED indicates signal equalised and 'SET'
DIMENSIONS	19" x 1.5U x 25mm (excluding BNC connectors)
MOUNTING	Via 2 x 3.5mm holes for convenient screw fixing

Ordering Information

For a quotation, further details or technical support and advice, contact us by phone, fax or email, quoting part number BH260. Contact details are below.

Addlestone Electronics Ltd, Church Lane, Bisley, Surrey. GU24 9EA

Tel: +44 (0)1483 480969 Fax: +44 (0)1483 797268

Email: Support@Addlestone-Electronics.co.uk Website: www.Addlestone-Electronics.co.uk